



The Busy Hour Call Attempts (BHCA) calculation for the Millennium with a System Controller II is 40,000¹. Below you will find the MTBF schedule for the Millennium.

Part Number	Description	MTBF Hours	MTBF Years
500117-000-101	System Controller II Card	99,940	11
500004-536-002	System Controller Card	91,463	10
500045-000-101	Common Services Card	169,765	19
500054-000-102	200W Power Supply	224,958	26
500054-000-103	400W Power Supply	224,958	26
500084-000-101	T1/ISDN PRI Card	142,401	16
500084-000-102	E1/ISDN PRI Card	142,401	16
500002-536-002	Digital Line Card	161,859	18
500012-536-002	Analog Line Card	135,205	15
500120-536-001	Analog Line Card II	163,175	18
500014-536-002	Analog Station Baby Board	788,923	90
500015-536-002	Analog Trunk Baby Board	1,257,324	144
500118-536-001	Analog Trunk Baby Board II	616,621	70
500017-000-101	Memory Card	1,215,599	139
500057-000-101	8-Slot Cabinet	1,750,700	200
500060-000-101	16-Slot Cabinet	978,474	112
5006CL-750-100	6-Button Telephone	260,947	29.8
5012CL-750-100	12-Button Telephone	223,912	25.6
5018CL-750-100	18-Button Telephone (4-wire)	204,699	23.4
5030CL-750-100	30-Button Telephone (4-wire)	171,187	19.5
5118CL-750-100	18-Button Telephone (2-wire)	187,483	21.4
5130CL-750-100	30-Button Telephone (2-wire)	159,461	18.2
9148CL-M0E-20E	48-Button Expansion Module	494,633	56.5
188990-0CL-PAK	2 x 24 LCD Display	788,955	90
189648-0CL-PAK	4 x 40 LCD Display	788,995	90

¹ Nominal rating only; actual capacity is dependent on the site's system hardware and software configuration.